

# LONCIN LC8000 Petrol Generator

E/START, 9AH Battery, Wheel Kit



With Loncin strong commercial engine. • AVR, Voltage adjust. • Low Oil sensor protection. • Cradle, Overall protection, easy move and storage. • Widely option for control panel, EU, US and AU receptacle for choice. • Self-start and remoter start as an optional. • Frequency, 50/60 Hz.

Model	LC8000
Voltage Outlets	(Sockets)(2 x 115V 32A 1 x 230V 21A)
Continuing time	(h)8New
Weight	Weight (Kg)86/89
Noise	Noise (dBA)?76
Displacement (cc)420	Starting system - Electric-start
Max Output (Kw)	6.5/7.0
Fuel Tank Capacity (L)	25
Rated Output (Kw)	6.0/6.5
Dimensions (mm)	680×540×540
Engine Model	G420F-1/G420FD-1